

MARKED-UP SPECIFICATION

## SPECIFICATION

## Title of the Invention

A MATRIX DISPLAY APPARATUS AND A DRIVING METHOD THEREOF

## Background of the Invention

~~(1) Field of the Invention:~~

The present invention relates to a matrix display apparatus and its driving method; particularly, to ~~the~~ a display apparatus and ~~the~~ a driving method capable of uniform brightness display, ~~furthermore as well as the~~ lowering of signal voltages and power consumption.

~~(2) Description of the Prior Art~~

One of the important ~~subjects~~ considerations in the design and operation of a liquid crystal display apparatus is the lowering of the driving voltage. Lowering the driving voltage brings about improvement of such factors as picture quality deterioration, ~~as~~ non-uniform brightness in a ~~the~~ display panel and power consumption reduction. Furthermore, the reliability of circuits in the display apparatus can be improved and ~~the~~ a lower price ~~of it~~ can be realized by downsizing the driving circuits. Especially, in using MOS-LSI ~~to a~~ techniques in the manufacture of the driving circuit, the price of the display apparatus is ~~more~~ lowered significantly because the area of a LSI chip can be made ~~into~~ small in size. As mentioned above, it is very ~~profitable~~ advantageous to the picture quality, the power consumption and the price to lower the driving voltage of a

liquid crystal display.

Various ~~method~~methods for lowering the driving voltages are ~~have been~~ presented. One of them is described in "SOCIETY FOR INFORMATION DISPLAY INTERNATIONAL SYMPOSIUM DIGEST OF TECHNICAL PAPERS, (1989), pp 242-244". The method described in ~~the~~this paper changes the scanning voltage and the counter electrode voltage ~~in-pulse-wise~~pulse-wise, in-phase and by the same amplitude, adjusting to the scanning timing for lowering the signal voltage(source voltage) of the voltages driving a TFT(Thin Film Transistor) liquid crystal matrix panel. By ~~the~~this method, the amplitudes of signal voltages can be ~~lowered~~, ~~but~~lowered, ~~but~~ the waveform distortion of the counter electrode voltages and ~~a~~the scanning voltage increases, since parasitic capacitances and resistances of the wiring increase due to an increase ~~of~~in the size of the liquid crystal panel. Therefore, the voltage applied to the liquid crystal changes depending ~~to~~on the pattern displayed on the panel, and ~~the~~a non-uniform brightness and ~~the~~a deterioration of picture quality occurs in the panel thereby. Especially, in a high resolution liquid crystal panel having about a thousand ~~of~~ scanning lines, ~~the~~the lines, the influences of the waveform distortion becomes severe and the picture quality deterioration occurs significantly due to a short scanning time of one line. Another method for lowering the signal voltage is also described in "SOCIETY FOR INFORMATION DISPLAY INTERNATIONAL SYMPOSIUM DIGEST OF TECHNICAL PAPERS, (1992), pp47-50". Although it is possible with this method to reduce the deterioration of the picture quality due to the waveform distortion of the scanning voltages and

the counter electrode voltages and to lower the driving voltage, direct current voltages are superposed on the voltages applied to the liquid crystal unless the parasitic capacitances between TFT terminals and the storage capacitances are uniform over the panel. Thereby, the phenomena of elongation of a display renewing ~~time~~, time, namely, ~~afterimage~~ an after-image occurs. The reliability of the liquid crystal decreases by the superposition of the direct current voltage on the liquid crystal. The storage capacitances and the parasitic capacitances have considerable non-uniformity in the panel when the panel size is as much as 10-15 inches, which is as large as the display panel size of personal computers. The non-uniformity is induced ~~by the cause that~~ because the accuracy of photo-mask adjustment and etching in the process of TFT ~~producing~~ production degrades ~~in proportion~~ proportionately as the panel size becomes large. So the reliability deterioration of the liquid crystal and the ~~afterimage~~ of the after-image phenomenon occurrence become more significant as the panel size increases. Other methods for decreasing the signal voltage are presented in Japan Laid Open 913/1990 and Japan Laid Open 145490/1992. ~~The~~ These methods do not resolve the problem of poor picture quality, such as the occurrence of a striped picture in the horizontal direction (referred to ~~the~~ as smearing).

## Summary of the Invention

### (1) ~~Object of the Invention~~

Objectives of the present invention are providing a display apparatus and a drive method thereof ~~for lowering~~ in which the signal voltages of the liquid

crystal matrix panel are lowered without deteriorating the picture quality, ~~for reducing non-uniformity of brightness over the panel caused by non-uniformity of output voltages of the drive circuit and the parasitic capacitances between terminals of TFTs~~ is reduced and ~~for preventing the smearing in a displayed picture~~ is prevented.

## ~~(2) Method Solving the Problems~~

In order to attain the above mentioned objectives, the present invention presents a matrix panel display apparatus having plural signal lines and plural scanning lines intersecting with each other and, near each intersection point, a picture element<sub>i</sub> including a picture element electrode, a counter electrode, a display medium between the two electrodes and a transistor for applying image signals from the signal line to the picture element electrode being controlled<sub>i</sub> based on the scanning signals from the scanning line, which ~~said apparatus~~ comprises:

means for generating auxiliary signals for increasing the effective voltages of the image signals and for applying the auxiliary signals to the picture elements<sub>i</sub> while each of the transistor is non-conducting and each of the picture ~~element elements~~ is not selected, and thereof.

The present invention also presents a matrix panel display apparatus having plural signal lines and plural scanning lines intersecting each other and, near each intersection point, a picture element<sub>i</sub> including a picture element electrode, a counter electrode, a display medium between ~~said the two~~ electrodes and a transistor for applying image signals from ~~said the~~ signal line to

~~said the~~ picture element electrode being controlled, based on said scanning signals from said scanning line, which ~~said the~~ apparatus comprises;

picture signal generating means in a signal circuit for dividing ~~the plural~~ picture elements selected at the same time into two groups and for applying a first picture signal group to the first group of picture elements and a second picture signal group, having ~~the a~~ polarity reverse to the ~~former~~ first picture signal group, to said second group of picture elements, and

bias signal generating means for applying first bias signals having ~~the a~~ polarity reverse to the first picture signal group to the first group of picture elements through storage capacitances in the first group of picture element, and second bias signals, having ~~the a~~ polarity reverse to the second picture signal group, to the second group of picture elements through storage capacitances in the second group of picture elements during a selection period of the first and second ~~group groups~~ of picture elements, ~~and a driving method thereof.~~

~~And A~~ liquid crystal is used as the display medium in the optimal embodiment.

#### Brief Description of the Drawings

Fig.1 shows a conceptual diagram of the ~~whole overall~~ matrix display apparatus ~~by of~~ the present invention.

Figs.2(a) and 2(b) show ~~example equivalent~~ circuits the picture elements in the matrix display apparatus.

Fig.3 shows ~~example a~~ waveform of the operations of the picture element

in the matrix display apparatus.

Fig.4 shows ~~the~~a first embodiment of the liquid crystal matrix display panel.

Fig.5 shows ~~the~~a second embodiment of the liquid crystal matrix display panel.

Fig.6 shows ~~an example~~ waveform of the driving timing of the liquid crystal matrix display panel.

Fig.7 shows ~~an example~~ the fundamental waveform of the voltage applied to the picture element in the present invention.

~~Fig.8~~ Fig. 8(a) shows an example is a schematic diagram of an equivalent circuit of a picture element and Figs, 8(b)-8(d) are waveform diagrams of the driving timing in the present invention.

Fig.9 shows ~~an example~~ is a characteristic diagram showing the relation between the effective voltage applied to liquid crystal ~~to~~ and the amplitude of a signal voltage (comparing two cases with and without the auxiliary signal).

Fig.10 shows ~~an example~~ is a diagram showing the relation between the brightness of a liquid crystal ~~to~~ and the amplitude of a signal voltage (comparing two cases with and without the auxiliary signal).

~~Fig.11~~ Fig. 11(a) shows the is a schematic diagram of an equivalent circuit and Fig. 11(b) shows the driving timing in ~~the~~ a third embodiment.

Fig.12 shows ~~the~~ is a schematic diagram of an equivalent circuit of the display picture element part in ~~the~~ a fourth embodiment.

Fig.13 shows ~~is~~ a schematic diagram of an example of an auxiliary signal

generation means in the fifth embodiment.

Fig.14 ~~shows the~~ is a schematic circuit constitution diagram of the ~~a~~ sixth embodiment.

Fig.15 shows ~~a the plane~~ view of the structure of the ~~a~~ picture element in the sixth embodiment.

Fig.16 ~~shows~~ is a diagram of the driving voltage waveforms in the sixth embodiment.

Fig.17 ~~shows~~ is a block diagram of the signal voltage generation part in the ~~a~~ seventh embodiment.

Fig.18 ~~shows the constitution~~ is a schematic diagram of the signal driving LSI in the ~~an~~ eighth embodiment.

Fig.19 ~~shows~~ is a diagram of the driving voltage ~~waveforms~~ waveforms in the ~~a~~ ninth embodiment.

Fig.20 ~~shows~~ is a diagram of the driving voltage ~~waveforms~~ waveforms in the ~~a~~ tenth embodiment.

Fig.21 ~~shows the~~ is a plane view of the structure of the ~~a~~ picture element in the ~~an~~ eleventh embodiment.

Fig.22 ~~shows the~~ is a schematic circuit constitution in the diagram of a twelfth embodiment.

Fig.23 ~~shows~~ is a diagram of the driving voltage waveforms in the twelfth embodiment.

Fig.24 ~~shows~~ is a schematic the circuit constitution in the diagram of a thirteenth embodiment.

Fig.25 ~~shows~~ is a diagram of the driving voltage waveforms in the a thirteenth embodiment.

Fig.26 ~~shows the plane constitution of the~~ is a diagram of a storage capacitance part in the a fourteenth embodiment.

Fig.27 ~~shows~~ is a diagram showing the strength of transmitted light with respect to the voltage applied to a liquid crystal.

Fig.28 ~~shows the~~ is a schematic drawing of an equivalent circuit of the two adjoining picture elements.

#### Detailed Description of the Embodiments

Hereinafter, details of the present invention is explained based on embodiments referring to drawings.

##### (Embodiment 1)

A conceptual figure of ~~a whole~~ the overall constitution of the display apparatus ~~by of~~ the present invention is shown in Fig.1. The display apparatus comprises a matrix panel 1 consisting of scanning lines 2, signal lines 3, and picture elements 4, provided at the intersection points ~~of~~ where the lines 2 and the lines 3 cross each other; a scanning circuit 5 and a signal circuit 6 for generating ~~the~~ predetermined voltages and applying them to the scanning lines 2 and the signal lines 3, respectively; a display control circuit 8 generating for supplying timing signals to the scanning circuit 5, and the signal circuit 6 and a an auxiliary signal for increasing the effective value of the signal voltages generating circuit 10; a system circuit 9 connected to the display control circuit



8<sub>i</sub>; the auxiliary signal generating circuit 10<sub>i</sub> and ~~a~~an auxiliary signal information generating circuit 11 connected to the auxiliary signal generating circuit 10 through ~~a~~an auxiliary signal line 13. As to the picture elements 4, any combination of switching elements ~~and~~using such display material as a liquid crystal, electroluminescence and so on is applicable<sub>i</sub> and so the invention is not restricted to any specific material combinations. And<sub>i</sub> the brightness or the gradation number of the picture elements is not restricted to any specific value. The auxiliary signal Vsub is inputted into a display part 7 consisting of the scanning circuit 5, the signal circuit 6 and the matrix panel 1 through ~~a~~an auxiliary signal inputting line 12. Examples of Vsub are described later. As shown in Fig. 1, the present invention is characterized by the ~~process~~method of selecting each picture element in turn by the scanning circuit 5, applying the picture signal voltage to the selected picture element by the signal circuit 6 (a first driving means), applying the auxiliary signal Vsub obtained by the auxiliary signal generating circuit 10 (a second driving means) to each picture element in the display part and displaying any pictures on the matrix panel 1 by driving the matrix panel 1 with the synthesized signals of ~~generated~~generated signals generated by the first and second driving means. The auxiliary signal information generating means 11 generates the information for ~~deciding~~determining the waveform of the auxiliary signal based on the environmental conditions<sub>i</sub> such as temperature, the display picture quality conditions<sub>i</sub> such as the brightness or the contrast of the picture elements<sub>i</sub> and so forth, and inputs the information into the auxiliary signal generating circuit 10. The information from the system circuit 9 may be

directly inputted into the auxiliary signal generating circuit 10.

An embodiment of the present invention ~~is~~ will be explained by taking a liquid crystal display apparatus as an example ~~in the followings~~. Equivalent circuit examples of the picture elements 4 in the liquid crystal display apparatus are shown in Figs. 2(a) and 2(b). The liquid crystal 17 is driven by ~~such a~~ switching element 16, such as a TFT. A MOS transistor, or a bipolar transistor besides a TFT, is also applicable ~~to~~ for use in the switching element. The storage capacitances 18 connected in parallel with the liquid crystal 17 ~~is~~ are not necessarily ~~not needed,~~ but providing such storage capacitances is convenient to constituting a flexible display apparatus. The difference between the equivalent circuit of Fig. 2(a) and that of Fig. 2(b) is ~~in~~ that a terminal of the storage capacitance 18 is connected to a storage capacitance voltage inputting terminal 20 ~~or in Fig. 2(a) and~~ to the scanning line 15 in Fig 2(b). Fig. 4 shows an embodiment of the present invention ~~of in~~ which the equivalent circuit of the picture elements 4 is ~~described as~~ that of Fig. 2(a). One picture element is ~~consisted~~ consists of the TFT 16, the liquid crystal 17 and the storage capacitance 18, and ~~the total all of the~~ picture elements are arranged ~~in the~~ as distributed dots ~~state of a~~ (m x n) matrix. A terminal of each liquid crystal 17 is connected to a respective TFT 16 and the other terminal of the liquid crystal 17 is connected to the auxiliary signal generating circuit 10. A terminal of each storage capacitance 18 is connected to a respective TFT 16 and the other terminal of the storage capacitance 18 is connected to the storage capacitance voltage inputting terminal 21. A power source 22 is connected to the storage

capacitance voltage inputting terminal 21. The above-mentioned liquid crystal display matrix panel ordinarily consists of plural signal lines and plural scanning lines wired on a substrate made ~~by such of a material~~ such as glass and which cross each other, picture element electrodes provided near each point of intersection, a first substrate on which the TFTs connected to the signal lines and the scanning lines are wired, a second substrate confronting ~~to~~ the first substrate and having ~~the~~ counter electrodes at the places opposite to the picture element electrodes on the second substrate, ~~made by of~~ made by such material as glass and the liquid crystal existing between the picture element electrodes and the counter electrodes. The counter electrodes are other side terminals of the liquid crystals 17 and are connected to the auxiliary signal generating circuit 10.

The operation of the picture element ~~is~~ will be explained ~~by~~ with reference ~~to Fig. 2~~ Fig. 2(a) and Fig. 3. When the scanning voltage  $V_g$  ( $V_{gh}$ ,  $V_{g1}$ ) ~~turns~~ rises to the high voltage  $V_{gh}$ , the TFT ~~becomes~~ switches to the ON state and the image signal voltage  $V_d$  applied to the signal line 14 is written into the liquid crystal 17. The picture element voltage  $V_s$  consequently becomes equal to the image signal voltage  $V_d$ . And, when the scanning voltage  $V_g$  ~~turns drops~~ to the low voltage  $V_{gl}$ , the TFT ~~becomes~~ switches to the Off state, but the state of the voltage  $V_s$  scarcely changes (holding state), but is ~~kept~~ maintained for a time by the effects of the electrostatic capacitance of the liquid crystal and the storage capacitance. As mentioned above, the liquid crystal is driven by the ON or OFF operations of the TFT. The brightness of the liquid crystal is controlled by changing the voltage level of the image signal voltage  $V_d$  during the time the

TFT stays ~~at~~in the ON state. The brightness of the liquid crystal 17 also depends on the voltage  $V_{lc}$  applied to the liquid crystal, namely, the voltage difference ( $V_{lc}=V_s-V_c$ ) between the picture element voltage  $V_s$  and the common voltage  $V_c$  applied to the common terminal 19<sub>1</sub> which is the terminal of the opposite side of the liquid crystal. Therefore, the brightness of the liquid crystal 17 can be controlled by the picture element voltage  $V_s$  or the common voltage  $V_c$ , and full color display is also possible by controlling each voltage  $V_{lc}$  corresponding to each color of R(red), G(green) and B(blue). The constitution of the panel is not restricted to one having ~~such as the two~~ opposite substrates as described in the embodiment 1.

(Embodiment 2)

Fig. 5 shows an embodiment of the present invention ~~of~~in which the equivalent circuit of the picture elements 4 is ~~described as that of~~ Fig. 2(b). One picture element ~~is consisted~~consists of the TFT 16, the liquid crystal 17 between a picture element 47-electrode and a counter electrode (not shown in the figure) and the storage capacitance 18, and all of the total picture elements are arranged ~~in the~~as distributed dots of a (m x n) matrix ~~states~~. A terminal of each liquid crystal 17 is connected to ~~each~~a respective TFT 16 and the other terminal of the liquid crystal 17 is connected to the auxiliary signal generating circuit 10. A terminal of each storage capacitance ~~28-18~~18 is connected to ~~each~~a respective TFT 16 and the other terminal of the storage capacitance ~~28-18~~18 is connected to ~~the~~a scanning line 15, which differs ~~differently~~ from the embodiment 1. Fig.7 shows an example of driving timing for the scanning

electrodes and the signal electrodes of the liquid crystal matrix panel, which is common to the embodiments 1 and 2. The scanning voltage  $V_{gl}$ - $V_{gn}$  are applied in turn to ~~n lines of the~~ scanning lines 15 for setting the TFTs to the ON state so ~~as that~~ the voltage  $V_{gh}$  ~~are~~ will be applied to the TFTs in succession for time  $T_L$ . The TFTs turn to the OFF state for the ~~time~~ $(T_F - T_L)$  time  $(T_F - T_L)$  when the scanning voltage is  $V_{gl}$ . The signal ~~voltage~~ voltages  $V_{d(l)}$ - $V_{d(m)}$  applied to the scanning lines 14 are changed in accordance with the scanning timing<sub>1</sub> and a method for applying the signal ~~voltage~~ voltages is not restricted to any specific ~~one~~ method. By the above mentioned driving method, ~~the~~ each signal voltage is written to ~~the~~ a liquid crystal 17 and the pictures are displayed. Fig.7 shows the fundamental waveform of the voltage  $V_{lc}$  applied to the liquid crystal 17 in the driving apparatus of the present invention. As mentioned above, the voltage  $V_{lc}$  is the difference between the output voltage  $V_s$  of a TFT 16 and the common voltage  $V_{c1}$  and the brightness of the liquid crystal 17 depends on the strength of  $V_{lc}$ , that is, the effective voltage during one period of  $T_2F$ . The voltage  $V_{lc}$  applied to the liquid crystal 17 consists of the voltage components  ~~$V_{N1}, V_{N2}$~~   $V_{N1}, V_{N2}$  outputted by the first voltage applying means, namely, the signal circuit 6, and the voltage components  ~~$V_{B1}, V_{B2}$~~   $V_{B1}, V_{B2}$  outputted by the second voltage applying means, namely, the auxiliary signal generating circuit 10. The voltages generated by the first voltage applying means drive the liquid crystal for the periods  $T_{N1}$ ,  $T_{N2}$ ,  $T_{N3}$  and  ~~$T_{N3}$~~  $T_{N4}$ , and the voltages generated by the second voltage applying means drive the liquid crystal for the periods  $T_{B1}$  and  $T_{B2}$ . The voltage components  ~~$V_{B1}, V_{B2}$~~   $V_{B1}, V_{B2}$  outputted by the second

voltage applying means are applied for the period when all TFTs in the effective picture elements of the matrix panel are in the OFF state. The voltages VN1, VN2 generated by the first voltage applying means shown in Fig. 7 change depending on the signal voltage Vd made by video signals. The length of each period of TN1, TN2, TN3 and TN4 when the voltages VN1, VN2 are applied to the liquid crystal is not restricted to any specific value. The waveform of the voltage made by the second voltage applying means is not restricted to any specific shape. That is, the periods TB1, TB2 and the heights of VB1, VB2 are discretionary, and the polarity of the pulse voltages applied to the liquid crystal is not restricted to either mono-polarity or bipolarity. And, applied frequency of the driving voltage ~~applying frequency produced~~ by the second voltage applying means is also discretionary. Further, the voltages produced by the first voltage applying means are shown as constant in Fig. 7 for the periods TN1, TN2, TN3 and TN4, but ~~the~~ these voltages may change with time without detracting from the utility of the present invention. The voltage waveform of the picture element by the above-mentioned driving method is explained by using ~~Fig.8~~ Figs. 8(a)-8(d). In ~~Fig.8~~ Fig. 8(a), the equivalent circuit of the picture element and in Figs. 8(b)-8(d) the ~~waveform~~ waveforms of each part of the circuit are shown. One picture element consists of the TFT 16, the liquid crystal 17, the storage capacitance 18, the common voltage inputting terminal 19 and the capacitance Cgs 30 between a gate and a source of the TFT. Waveform examples of the voltage driving the circuit and each part of the circuit are shown by the waveforms A, B and C in Figs. 8(b)-8(d), respectively. The waveform A shows

the common voltage  $V_c$  and one pulse having the amplitude of  $\pm V_{CN}$  is generated as an auxiliary signal during one frame. The waveforms B show waveforms of the scanning voltage  $V_g$ , the image signal voltage  $V_d$  and the source voltage  $V_s$ . ~~And the~~ The waveform C is a waveform of the voltage  $V_{lc}$  which is the difference voltage between the source voltage  $V_s$  and the common voltage  $V_c$ . As shown in the waveforms B, the source voltage  $V_s$  becomes nearly equal to the signal voltage  $V_d$  within the period  $T_L$  when the TFT 16 turns to the ON state. After the period, the TFT turns to the OFF state and the written voltage is kept held. Strictly describing speaking, the source voltage  $V_s$  slightly decreases by a resistance of the liquid crystal and ~~a~~ an OFF current flowing during the OFF state of the TFT. And, the source voltage  $V_s$  changes by  $\pm \Delta V_s$  as shown in ~~the figure~~ when the common voltage  $V_c$  changes ~~by~~ due to the addition of the auxiliary signal  $V_{sub}$  ~~addition~~ in the OFF state of the TFT. The change of  $\Delta V_s$  is described by Eq.(1).

$$\Delta V_s = V_{CN} \cdot (C_s + C_{lc}) / (C_{gs} + C_s + C_{lc}) \quad \dots\dots(1)$$

~~,where~~ where  $V_{CN}$  is ~~an~~ the amplitude of the auxiliary signal,  $C_{gs}$  is the parasitic capacitance,  $C_s$  is the storage capacitance and  $C_{lc}$  is the liquid crystal capacitance. And, the amplitude of the bias voltage  $V_B$  is described by Eq.(2)

$$V_B = V_{CN} - \Delta V_s \quad \dots\dots(2)$$

By applying the bias voltage having the amplitude of  $V_B$  given by Eq.(2), the effective voltage applied to the liquid crystal is higher than the amplitude  $V_{sig}$  given by the image signal voltage  $V_d$  without applying the bias voltage. That is, a ~~the-higher~~ effective voltage than that ~~voltage~~ inputted only by the outer video

signals can be obtained. The effective value of the applied voltage to the liquid crystal depends on the amplitude and the width of the auxiliary pulse signal  $V_{sub}$  and the effective voltage becomes higher in accordance with an increase of the amplitude and the width of a pulse. Fig. 9 shows the relation between the image signal voltage amplitude and the effective voltage by comparing two cases with and without the auxiliary signal. Further, Fig. 10 shows the relation between the brightness of the liquid crystal and the image signal voltage amplitude. As shown by the curve B in Fig. 9,  $V_{os}$  is the effective voltage when  $V_{sig}$  equals 0. Although the effective voltage becomes higher in accordance with an increase of the amplitude  $V_{sig}$ , the ratio of the effective voltage deviation to the deviation of the image signal voltage amplitude ( $=\Delta V_{dr}/\Delta V_{sig}$ ), namely, the gradient of the curve decreases in accordance with an increase of the effective voltage, as compared with the characteristics of the prior driving method, namely, the driving method without the auxiliary signal applying (the curve A). ~~Therefore~~Therefore, as shown by the curve B in Fig.10, the ratio of the liquid crystal brightness change to the change of the image signal voltage amplitude becomes smaller, that is, the characteristics of liquid crystal becomes more gentle, as compared with the characteristics of the prior driving method (the curve A). And, the image signal voltage amplitude for getting-obtaining the same brightness of the liquid crystal decreases, as compared with the prior driving method. The brightness and the contrast of a display panel is made ~~uniform~~ considerably more uniform by reducing the brightness variation due to the non-uniformity of the voltage written to a liquid crystal caused by the parasitic



capacitance between the terminals of the TFTs and by the variation of the output voltage of the signal circuit. Thereby, it becomes possible to attain the a high quality picture display, to downsize the driving circuit, and to lower the power consumption. In Eq.(I), if  $(C_s+C_{lc})/(C_{gs}+C_s+C_{lc}) \leq 0.5$ , then  $\Delta V_s \leq V_{CN}/2$ , which profitably stabilizes the characteristics of the TFT due to the source voltage fluctuations.

(Embodiment 3)

~~Fig. 11~~ Fig. 11(a) shows an equivalent circuit of a picture element and Fig. 11(b) is a waveform diagram of the driving timing in another embodiment. The embodiment corresponds to Fig. 2(b), and in which one terminal of the storage capacitance is connected to the source terminal S and the other terminal is connected to the scanning line 15 adjoining the scanning line connected to the TFT 16. The auxiliary signal Vsub is applied to the common terminal 19 in the embodiment shown in Fig. 5, having the same equivalent circuit shown in Fig. 2(b); on the other hand, the auxiliary signal is applied through the scanning line 15 in the present embodiment. The auxiliary signal Vsub of an amplitude VCN smaller than the voltage Vgh besides Vgh, Vgl for turning ON or OFF each TFT is applied to the scanning voltage Vg(i). The voltage Vgh, applied as the scanning voltage Vg(i), is transmitted to the source terminal S of the TFT 16 and, synchronizing it, the source voltage Vs is generated. When the source voltage Vg(i+1) becomes Vgh and the TFT 16 turns to the ON state, the image signal is written to the liquid crystal 17 through the signal line 14 and the source voltage Vs becomes the same voltage as the image signal voltage. ~~Nextly~~

Thereafter, the scanning voltage  $V_{g(i+1)}$  decreases to  $V_{gl}$  and the TFT 16 turns to the OFF state, but the written image signal voltage is kept held. If the auxiliary signal  $V_{sub}$  is applied to the scanning voltage  $V_{g(i)}$  in-during the period, the auxiliary signal is transmitted to the source terminal S of the TFT 16 through the storage capacitance 18 and the bias signal is applied to the source voltage, synchronizing ~~to it with~~ the auxiliary signal  $V_{sub}$ , as shown in the figure. The effective voltage applied to the liquid crystal 17 increases and the same effect as the driving method shown in Fig.8 is obtained thereby.

(Embodiment 4)

Fig.12 shows another ~~embodiment in~~ arrangement of the picture element part. The picture element consists of the scanning line 15, the signal line 14, the TFT 16, the storage capacitance 18 and an auxiliary signal transmitting means 37. The auxiliary signal transmitting means 37 may be composed, for example, ~~by using of~~ a condenser  $C_{ac}$  for passing ~~alternative~~ alternating current components and for cutting off direct current components; although ~~and the~~ ~~constitution for realizing the~~ auxiliary signal transmitting means is not restricted to a condenser ~~any specific one~~.

(Embodiment 5)

Fig. 13 shows an ~~embodiment as to~~ example of the auxiliary signal generating circuit 10 and the auxiliary signal information generating means 11 in Fig. 4 and Fig. 5. In ~~the embodiment~~ this example, the auxiliary signal information generating means comprises a variable resistance 32. It is preferable that the variable resistance 32 is provided at such places as the

outskirts of a display apparatus so as to make is possible to change ~~capable of changing~~ the resistance easily. Thereby, it is possible to easily change the brightness, contrast and view angle of the displayed picture.

Embodiments effective for resolving mainly such non-uniform display problems as the smearing in the displayed picture are mentioned in the ~~followings~~ following.

(Embodiment 6)

Firstly, the mechanism of the smearing phenomena is briefly explained. The equivalent circuit of ~~the two adjoining picture element~~ elements spaced in the horizontal direction of the active matrix liquid crystal display apparatus is shown in Fig. 28. The picture element electrodes are connected to the source electrodes of the TFTs 16a and 16b, and the picture element electrodes, the counter electrodes and the liquid crystal layers between both the electrodes form the liquid crystal capacitances  $C_{lc}$  17a and 17b. The storage capacitances  $C_s$  18a and 18b are connected to the source electrodes of TFTs 16a and 16b. The counter electrode is common to all picture elements and the earth electrode of the storage capacitance is connected to the (i-1)th scanning line 2 ( or the storage line 8 ). Since the counter electrode potential  $V_c$  is common through all picture elements and the earth potentials of the storage capacitances (referred to the storage line potential)  $V_s$  have the same potential, or so at least at the storage line above one line of the line selected presently, the bias voltages of the same polarity are applied to all the picture elements, at least, above one line. And, to the odd number lines and the even number lines, the same polarity of

the signal voltages  $V_d(2j-1)$  and  $V_d(2j)$  are applied, respectively. Thereby, the noise effects become significantly significant, since the noises to the storage line potentials  $V_s$  and the counter electrode potentials  $V_c$  induced by changes of the signal voltages  $V_d(2j-1)$  and  $V_d(2j)$  through the capacitances 100a and 100b between the signal line 3 and the counter electrode and the crossing capacitances 101a and 101b between the signal line 3 and the storage line 28 have the same polarity in the above-mentioned situations. The time that the changing potentials of  $V_c$  and  $V_s$  revert to the original potential value depends on the change amplitude of the signal voltage  $V_d$  and the load conditions of the line above one line. And, since each picture element at the line above one line is charged by voltages of the same polarity of voltages, the directions of inflow and outflow of the charge current ion become the same and the charge currents  $I_{on}$  flow into the counter electrodes and the storage lines ~~of which whose~~ potentials are returning to a stable state, which prevents the potentials  $V_s$  and  $V_c$  from reverting to the original value. The voltage written to the picture element is affected by the remaining quantity of the above-mentioned potential variation by the time the TFTs 16a and 16b turn to the OFF state, which affects the variations of the picture element brightness, since the voltage written to the picture elements are determined by the picture element electrode potentials, the counter electrode potentials  $V_c$  and the storage line potential  $V_s$  at the time the TFTs 16a and 16b turn to the OFF state. The variation in the magnitudes of the signal voltages  $V_d$ , the load conditions of the lines and the charge currents which determine the remaining quantity of the above-mentioned potential

variation at the time the TFTs turn to the OFF state depend on the display picture pattern at the line above one line. Consequently, the poor picture quality, such as the striped picture in the horizontal direction, namely, the smearing, which is a sort of cross talk, is brought about. The embodiment shown hereafter considerably reduces the smearing phenomena by dividing the picture elements selected at the same time into two groups and writing the image signal voltages having ~~the~~ a polarity reverse to each other into the first group picture element electrodes and the second group picture element electrodes, respectively, because the potential variations(noises) of the counter electrodes and the storage line (or the scanning line), cancel each other or decrease, and the charge voltages written into the picture elements are well stabilized due to the short time of potential stabilizing.

Fig. 14 shows the circuit constitution of the embodiment and Fig. 15 shows an example in plane views of the structure of the picture element. As shown in Fig. 14, the picture elements between the (i-1)th scanning line and the (i)th scanning line are divided into two groups, that is, ~~the~~ an odd column group and ~~the~~ an even column group. The gate electrodes of the TFTs of the odd column group are commonly connected to the (i-1)th scanning line and the earth electrodes of the storage capacitances in the same group are commonly connected to the (i)th scanning line. The gate electrodes of the TFTs of the even column group are commonly connected to the (i)th scanning line and the earth electrodes of the storage capacitances in the same group are commonly connected to the (i-1)th scanning line. ~~The~~ In this arrangement, (i) is any integer

satisfying the condition:  $2 \leq i \leq M$  ( $M$ : ~~the a~~ whole number of the scanning lines). As far as the connective arrangement of the TFTs to the scanning lines is concerned, the TFTs of the odd column group are connected to the lower side scanning line and the TFTs of the even column group are connected to the upper side scanning line, that is, the TFTs are connected in a zigzag state to a scanning line. The driving LSI 5 for scanning is connected to the scanning lines and the driving LSI 6 of 5 V withstanding voltage for generating the image signal voltages is connected to the signal lines, in the display panel having the above-mentioned constitution. Fig. 16 shows waveforms for driving the display panel of ~~the this~~ embodiment which are the waveforms of the scanning voltages  $Vg(i-1)$ ,  $Vg(i)$  and  $Vg(i+1)$  applied to the three adjoining scanning lines, namely, the  $(i-1)$ th, the  $(i)$ th and the  $(i+1)$ th scanning linelines, and shows the counter electrode potential  $Vc$ , the signal voltage  $Vd(2j-1)$  applied to the  $(2j-1)$ th line, namely, the odd column signal line and the signal  $Vd(2j)$  applied to the  $(2j)$ th line, namely, an even column signal line. The scanning signals  $Vg$  applied to each scanning line consist of scanning pulses and bipolar bias pulses of the amplitude  $VB^*$  superposed before and after the scanning pulse (the positive pulse amplitude may be different from the negative pulse amplitude). Therefore, as the driving LSI for scanning, ~~such a an~~ LSI as which can generate at least four values of voltages is used. Since the liquid crystal must be driven by ~~a an~~ alternating current voltage, ~~the voltages having the a~~ polarity reverse to each other are applied to the liquid crystals in the odd frame and in the even frame, respectively. As shown in Fig. 16, in the odd frame, the waveform superposed

by a positive polarity bias pulse of the  $1H$  width before  $1H$  of the scanning pulse of the  $(1H+td1)$  width and a negative polarity bias pulse of the  $(1H+td2)$  width right after the scanning pulse is applied; and in the even frame, the waveform superposed by a negative polarity bias pulse of the  $1H$  width before  $1H$  of the scanning pulse of the  $(1H+td1)$  width and a positive polarity bias pulse of the  $(1H+td2)$  width right after the scanning pulse is applied. The rising of the scanning pulse applied to the  $(i)$ th scanning line must be done after the scanning pulse applied to the  $(i-1)$ th scanning line has dropped sufficiently ( the TFT completely turns to the OFF state. ) and the necessary dropping time is described by  $td1$ . And applying, application of the scanning pulse to the  $(i)$ th scanning line must be done after the scanning pulse of the same scanning line has dropped sufficiently, and the necessary dropping time is described by  $td2$ . For example,  $3\ \mu s$  is adopted as the value of  $td1$  and  $td2$ . Further, the signal voltage  $V_d$  must be changed after the scanning pulse applied to the former scanning line has dropped sufficiently, when signals are written into picture elements selected by the next scanning line, after the writing of image signals into the picture elements selected by a scanning line is finished. The necessary dropping time is assumed as to be the same time as  $td2$ . The amplitude  $VB^*$  of the bias pulse is set up as follows, so as that the maximum amplitude  $V_{dpp}$  ( $V_{dpp}=V_{max}-V_{th}$ ) of the voltage applied to the scanning line becomes minimum, corresponding to the characteristics curve of transmitted light strength-voltage applied to a liquid crystal, as shown in Fig. 27. The voltage actually applied to the liquid crystal is given by the following equation from the bias voltage  $VB^*$

applied to the scanning line;

$$V_B = (V_{\max} + V_{th})/2 \quad \dots\dots(3)$$

where  $V_{th}$  is the optical threshold voltage in the characteristics curve of transmitted light strength-voltage applied to the liquid crystal shown in Fig. 27, and  $V_{\max}$  is the voltage for obtaining a black color display in a normally opened state. Since the counter electrode potential  $V_c$  is constant in the embodiment,  $V_B^*$  for obtaining the bias voltage  $V_B$  is described by the following equation:

$$V_B^* = V_B (C_s + C_{lc} + C_{gs})/C_s \dots\dots(4)$$

where  $C_{gs}$  is the gate-source capacitance of the TFT. For example, if the liquid crystal ~~of in~~ which  $V_{th}$  is 2 V is used and  $V_{\max}$  is set, then  $V_{dpp} = 3$  V and  $V_B = 3.5$  V are obtained. ~~Therefore~~ Therefore, if in the picture element where  $C_s = 3$   $C_{lc}$  is designed, the amplitude  $V_B$  of the bias voltage is obtained since  $C_{gs} \ll C_s, C_{lc}$ . In this case,  $V_{dpp} < 5$  V, and so cheap LSIs of 5 V withstanding voltage can be used, and, further more, ~~the a~~ a contrast ratio of 60 can be obtained. In the waveforms in Fig. 16, in the odd frame, when the scanning pulse is applied to the (i)th scanning line, the positive bias voltage  $V_B^*$  is applied to the (i+1)th line, and ~~the a~~ a negative bias voltage ( $-V_B^*$ ) is applied to the (i-1)th scanning line. And, ~~the voltages of the~~ having a polarity reverse to each other  $\pm V_{sig}^*$  ( $= \pm V_B^* \pm V_d$ : double sign is in the same order.) are written into the storage capacitances of the odd column picture elements and the even column picture elements, respectively, by applying the positive signal voltage ( $+V_d$ ) to the even column signal lines and the negative signal voltage ( $-V_d$ ) to the odd column signal lines. In the picture elements selected at the same time, the positive bias



voltage and the negative signal voltage are applied to the odd column picture element, and the negative bias voltage and the positive signal voltage are applied to the even column picture elements. Each polarity of the bias voltage and the signal voltage is reverse to each other. And, when the potentials of the (i-1)th, the (i)th, and the (i+1)th scanning ~~line-lines~~ turn to the OFF level, the image signal voltages ~~of the~~ having a polarity reverse to each other  $+V_{sig}(=+V_B+V_d$ : double sign is in the same order.) are applied to the odd column picture elements and the even column picture elements, respectively, and the light transmission rate is controlled thereby. The voltage  $V_d$  expresses the potential deviation from the central voltage  $V_{d-center}$ , and its value is 1.5 V in black color displaying and -1.5 V in white color displaying. The polarity of the bias voltages and the signal voltages in the odd frame ~~turn over~~ reverse in the even frame. Since, in the embodiment, the ~~constitution having the~~ TFTs are arranged in a zigzag state at a scanning line, the sequence means fitted to such TFT arrangement for addressing the image signal data is provided in the image signal generating part. As mentioned above, ~~the~~ a good contrast ratio can be obtained, while the voltage amplitudes applied to the signal lines are decreased. Further, by ~~turning over~~ reversing the polarity of the signal voltages written into the picture elements in every column in a frame, the noises induced within the period  $1H$  at the potentials of the counter electrodes and the scanning line through the capacitances between the signal electrodes and the scanning line induced by change of the signal voltage  $V_d$  cancel each other between the adjoining picture elements in the horizontal direction. The noises induced within

the period  $1H$  at the counter electrodes by the current flowing into the counter electrodes through the liquid crystal capacitances due to the one way nature of the charge current ~~in~~ during the image signal writing will also cancel each other between ~~the~~ adjoining picture elements. And, as far the effects of the noises induced within the period  $1H$  at the potential of the scanning line by the current flowing into the scanning line through the storage capacitances due to the one way nature of the charge current in the image signal writing is concerned, the ability ~~of absorbing~~ to absorb noises increases by about two times, and the potential stabilizing time ~~become~~ becomes shorter, since the noise effects decrease more rapidly, ~~by the constitution of the~~ in this embodiment. Thereby, the dependency of the voltages written into the picture elements on the display signal pattern in the horizontal direction is reduced, and consequently, the smearing generated in the horizontal direction is considerably decreased. In the embodiment, a-Si TFTs are used as transistor elements, but the transistor elements ~~is~~ are not restricted to any specific type. For example, p-Si TFT or MOS FET devices may be used. Although the picture elements are divided into ~~the~~ an odd column group (the first group) and ~~the~~ an even column group (the second group) in the embodiment, the dividing ~~way~~ is not restricted to any specific ~~way~~ arrangement, and only two group dividing is necessary. For example, by bundling the consecutive  $n$  columns ( $n=1,2,3,\dots$ ) in one unit, dividing the units into ~~the~~ an odd number unit group and ~~the~~ an even number unit group is a ~~usable way~~ useful arrangement. In ~~the~~ this way, the bias voltages of the having a polarity reverse to each other through the storage capacitances and ~~the~~

signal voltages ~~of the~~ having a polarity reverse to each other are also applied to the picture elements of the first group and the second group, respectively. And, the bias voltage and the signal voltage applied to the same picture element have ~~the a~~ polarity reverse to each other. Such a grouping ~~way as in which~~ the number of the picture elements in each group is equal makes the noise canceling effect great, and the grouping ~~way that~~ arrangement in which  $n=1$  makes the effect maximum.

(Embodiment 7)

The constitution of the embodiment is the same as the embodiment 6 ~~except the matters mentioned in~~ for the following.

~~The In~~ embodiment 6 has the constitution having, the TFTs are arranged in a zigzag state at a scanning line and the sequence means fitted to such TFT arrangement for addressing the image signal data is provided in the image signal generating part. But, for making the display apparatus compatible with the signal generating part of a ~~usual~~ conventional personal computer, it is necessary to delay the odd column image signal data after the even column image signal data by the period 1H in the above-mentioned constitution of the embodiment 6. In the present embodiment, as shown in Fig.17, the even column image signal data outputted from the controller 8 are held on the bus line for inputting the data to the lower signal driving LSI 6 during the period 1H by using the 1/2 line memories 62 and inputted to the lower signal driving LSI 6. And, the non-interlaced signals are used as the image signal data. Although ~~the~~ 1/2 line memories are used in the embodiment, the memories 62 may be provided in the

controller S. The embodiment has the effects that the display apparatus of the embodiment can be connected to a general purpose image signal generating part of ~~such a computer,~~ such as a personal computer<sub>1</sub> in addition to the effects of the embodiment 6.

(Embodiment 8)

The constitution of the ~~this~~ this embodiment is the same as the embodiment 6 except the ~~matters mentioned in~~ for the following.

For matching the matrix constitution having the TFTs arranged in a zigzag state at a scanning line, a signal driving LSI 6 is used. The signal driving LSI 6 has a shift resistor or a latch 71 for ~~memorizing~~ storing the image signals in turn, a latch 73 for ~~memorizing~~ storing the image signals Vd fitting to the horizontal synchronizing signal, latch 72 capable of selecting a latching or a passing through mode<sub>1</sub> and a sample hold circuit or a voltage selector 74 for generating the image signal ~~74~~. By setting the latch 72 to the passing through mode in the upper signal driving LSI and to the latching mode in the lower driving LSI, the image signals Vd from the lower driving LSI is are delayed by the period 1H. The present embodiment<sub>1</sub> as well as the embodiment 7<sub>1</sub> has the effects that the display apparatus of the embodiment can be connected to a general purpose image signal generating part of ~~such a computer~~ such as a personal computer<sub>1</sub> in addition to the effects of the embodiment 6.

(Embodiment 9)

The constitution of the embodiment is the same as the embodiment 6 except the ~~matters mentioned in~~ for the following.

In Fig.19, the driving waveforms are shown in the embodiment. The scanning lines are scanned at every two lines (interlaced). Thereby, it is not necessary to wait for the sufficient dropping of the previous scanning pulse for generating the next scanning pulse and the waiting period  $td1$  shown in Fig.16 is not necessary. And, the capacitances of the liquid crystals and the storage capacitances ~~is~~ are charged enough, which prevents ~~the~~ a poor charging, since the scanning pulse width can be increased by the period  $td1$  (for example,  $3\mu s$ ) by the above-mentioned scanning. The image signals of  $1/2$  frame in the even column signal lines are ~~memorized~~ stored and outputted to each even column signal line by ~~memorizing~~ storing the interlaced signals using the  $1/4$  frame memories in the embodiment. The present embodiment, in addition to the effects of the embodiment 6, has the effects that the display apparatus decreases the poor charging and ~~suppresses the~~ ensures a brightness uniformity.

(Embodiment 10)

The constitution of the embodiment is the same as the embodiment 6 except ~~the matters mentioned in~~ for the following.

In the embodiment, the polarity of the signal voltages is ~~turned over~~ reversed at every column and the polarity of the bias pulses is also ~~turned over~~ reversed at every column. The generated waveforms are shown in Fig.20. By ~~turning over~~ reversed the polarity of the image signal voltages at every column, the noises induced by the signal voltages  $V_d$  in one frame at the picture element voltages, through the capacitances between the picture element electrodes and

the signal lines<sub>1</sub> are averaged over the frame<sub>1</sub> and the vertical smearing depending on the display image pattern in the column direction ~~besides<sub>1</sub> in~~ addition to the horizontal smearing<sub>1</sub> can be also suppressed. The present embodiment, in addition to the effects of the embodiment 6, has the effects that the display apparatus suppresses also ~~the~~ any vertical smearing.

(Embodiment 11)

The constitution of the embodiment is the same as the embodiment 6 except ~~the matters mentioned in~~ for the following.

The plane constitution of the picture elements in the embodiment is shown in Fig.21. The picture element electrode 50<sub>1</sub> which has two aperture parts<sub>1</sub> is formed at the both sides of a TFT in the column direction by crossing the TFT. Thereby, the picture elements scanned at the same scanning line are partially overlapped by each other<sub>1</sub> and, at the same time, the storage capacitances Cs at the odd column and the storage capacitances Cs at the even column are connected to ~~the~~ different scanning lines, respectively. The present embodiment has the same ~~constitution of electrical circuit~~ arrangement as the embodiment 6<sub>1</sub> but ~~the~~ a spatial constitution different from that of the embodiment 6. The present embodiment can display the display image pattern correctly without shifting each phase of the signal voltages of the odd column and the even column by the period 1H, by remedying spatially the effects by the time lag of the period 1H between the signal voltages of the odd column and the even column. The present embodiment, in addition to the effects of the embodiment 6, has the effects that the display apparatus can present ~~the~~ a

lower cost module<sub>1</sub> comprising the controllers and so forth<sub>1</sub> since the phase shifting of the signal voltages of the odd column and the even column by the period 1H is not needed<sub>1</sub> and the 1/2 line memories or the 1/4 frame memories do not have ~~not~~ to be provided as in the embodiments 7 and 9.

(Embodiment 12)

The circuit diagram of the active matrix liquid crystal display apparatus of the embodiment is shown in Fig.22. By forming the counter electrodes in a stripe state and grouping them into ~~the~~ odd column electrodes and ~~the~~ even column electrodes, each group is commonly connected to the first bias circuit 53 and the second bias circuit 54, respectively. And<sub>1</sub> the storage capacitances Cs are formed by the gate insulating film sandwiched between the wiring (storage wiring) constituted by the same material and layer as the scanning wiring and the picture elements, and the odd column storage capacitances are commonly connected to the storage lines S1 and the even column storage capacitances are commonly connected to the storage lines S2. All the storage lines S1 are connected together and to the first bias circuit 53, and all the storage lines S2 are connected together and to the second bias circuit 54. Although the picture elements at the same line are divided into ~~the~~ an odd column group (the first group) and the even column group (the second group) in the embodiment, the dividing way manner in which the columns are divided is not restricted to any specific way<sub>1</sub> and only a two group dividing of the picture elements selected at the same time and on the same scanning line is necessary. Particularly, if the column picture elements are divided two groups in every column<sub>1</sub> as described

in ~~the~~ this embodiment, the flickering is most effectively suppressed due to a short ~~turning-over~~ reversing period of the polarity. However, the column grouping in every column brings about ~~the~~ a high probability of short-circuits, so it is preferable to determine the number of ~~burdening~~ the grouping of the columns by considering the trade-off between the suppression of flickering ~~suppressing~~ and the reduction in short circuit decreasing occurrences. In Fig. 23, the driving waveforms are shown. The rectangular waveform voltages  $V_s$  and  $V_c$  having the amplitude  $2 V_B^*$  outputted from the first and the second bias circuit are applied to the storage lines and the counter electrodes ~~by the~~ in alternating period ~~periods~~ at two frames. The phase shift between the voltage waveforms outputted from the first bias circuit 53 and the second bias circuit 54 is 180 degrees ( each polarity of the voltages is reverse to each other-) and the voltages of the polarity reverse to each other are superposed ~~to on~~ the signal voltages of the odd column and the even column picture elements, respectively. Since the liquid crystal needs to be driven by an alternating current voltage, ~~the~~ voltages ~~of the~~ having a polarity reverse to each other are superposed ~~to on~~ the liquid crystals in the odd frame and in the even frame, respectively. The polarity ~~turning-over~~ reversing is done during the period of a retrace line. And, the signal voltages outputted to the odd column and the even column signal lines have the polarity reverse to each other and are ~~turned-over~~ changed in every frame. The bias pulse amplitude  $2 V_B^*$  is set according to the characteristics curve of transmitted light strength-applied voltage so ~~as that~~ the bias voltage  $V_B$  is within the range  $V_{th} \leq V_B \leq V_{max}$  and the maximum amplitude  $V_{dpp}$  of the voltages



applied to the signal lines is the minimum value ( $V_{dpp}=V_{max}-V_{th}$ ). First, the amplitude  $2 V_B$  is determined by Eq.(3) similarly in the embodiment 6. Let  $C_{gs} \ll C_s, C_{lc}$  ( $C_{gs}$ : capacitance between TFTs,  $C_s$ : storage capacitance,  $C_{lc}$ : liquid crystal capacitance), and the bias voltage  $V_B (=V_B^*)$  is given by the bias pulse amplitude  $2 V_B^*$  as the voltage applied to the liquid crystal. For example, by using ~~the a~~ liquid crystal ~~of in~~ which  $V_{th}$  is 2 V and setting  $V_{max}=5$  V,  $V_{dpp}=3$  V and  $V_B=3.5$  V are obtained. And, the bias pulse amplitude  $2 V_B^*$  is set to 7 V. For turning over the polarity of the odd column signal voltage and the polarity of the even column signal voltage in every column, respectively, it is ~~adaptable~~ possible that, by dividing the signal driving LSI into ~~the an~~ upper one and ~~the a~~ lower one and by connecting the odd column signal lines to the upper signal driving LSI, and the even column signal lines to the lower signal driving LSI, the voltages outputted from the upper signal driving LSI and the lower signal driving LSI have ~~the~~ polarity reverse to each other. By controlling the polarity of the image signal voltages so as ~~as that~~ the voltages  $+V_{sig}(=V_B+V_d$ , double sign is in the same order-) are applied as the image signal voltage, the polarity of the image signal voltages is ~~turned over~~ reversed in every column, where  $V_d$  is the potential difference from the center voltage  $V_{d-center}$ , and its value is 1.5 V in black color displaying and -1.5 V in white color displaying. And, by ~~the this~~ embodiment, the contrast ratio of 60 is gained; and, further, ~~the~~ LSIs of 5 V withstanding voltage can be used, since  $V_{dpp}=3$  V and the cost spent for LSIs can be also reduced.

## (Embodiment 13)

The circuit diagram of the active matrix liquid crystal display apparatus of ~~the~~ this embodiment is shown in Fig. 24. The counter electrode is formed all over the picture elements. The storage capacitances Cs are formed by the storage lines, the picture element electrodes and the gate insulating film between them, and the odd column picture elements are connected to the storage lines S1 and the even column picture elements to the storage lines S2. The storage lines S1 and S2 are respectively connected to the bias signal driving LSI 40 in every column thereof and is insulated electrically. Fig.25 shows the driving waveforms of the embodiment. The bias pulses from the bias signal driving LSI 40 are applied to each of the storage lines when the line is selected. So, since voltages having a ~~as the voltage of the~~ polarity reverse to each other are superposed ~~to-on~~ on the picture elements of the odd column and the even column, respectively, the polarity of the bias pulses applied to the storage lines S2 is made reverse to the polarity of the bias pulses of the storage lines S1. And, ~~the bias voltages of the~~ having a polarity reverse to each other are applied to the liquid crystals in the odd frame and in the even frame, respectively, since the liquid crystal needs to be driven by an alternating current voltage. Since the counter electrode is connected in common to all of the picture elements in ~~the~~ this embodiment, the counter electrode potential is set constant and ~~the two~~ voltages of ~~the~~ different polarity are supplied as the bias voltage only through the storage capacitances. The bias pulse amplitudes  $VB^*(+)$  and  $VB^*(-)$  are set as follows. First, the bias voltages applied to the liquid crystals are set by Eq.(3)

similarly in to the embodiment 6. And, ~~letting~~  $VB^{*}(+) + VB^{*}(-) = 2VB^{*}$ , particularly  $VB^{*}(+) = VB^{*}(-) = VB^{*}$ , the relation between  $VB$  and  $VB^{*}$  is given by Eq.(4). For example, by using the liquid crystal ~~of~~ in which  $V_{th}$  is 2 V,  $VB = 3.5$  V is obtained. And, by using ~~the~~ a picture element ~~of~~ in which  $C_s$  equals 3  $C_{lc}$ ,  $VB^{*}$  is set to 4.7 V for setting to  $VB$  3.5 V, since  $C_{gs} \ll C_s, C_{lc}$ . By controlling the polarity of the image signal voltages so ~~as~~ that the voltages  $+V_{sig}$  ( $=VB \pm V_d$ , double sign is in the same order-) are applied as the image signal ~~voltage~~ voltages, the polarity of the image signal voltages is also ~~turned over~~ reversed in every column in the present embodiment ~~similarly in~~, similar to the embodiment 12. And, the bias pulses must be dropped after the TFTs ~~of~~ coupled the lines to which the pulses are applied completely turn to the OFF state. The maximum delay time  $t_d$  is, for example, 3  $\mu s$  and the bias pulse width is set to  $(1H + t_d)$ . And, by ~~the~~ this embodiment, ~~the~~ a contrast ratio of 60 is ~~gained~~ obtained, and, further, ~~the~~ LSIs of 5 V withstanding voltage can be used since  $V_{dpp} < 5$  V. Further, by the constitution of the present embodiment, the product process for dividing the counter electrodes is not needed, so the panel product cost can be reduced by a throughput improvement, a decrease of material cost ~~such as~~ in the use of resist material can be obtained, and yield rate improvement can be experienced.

(Embodiment 14)

The constitution of the embodiment is the same as the embodiment 13 except ~~the matters mentioned in~~ for the following. Fig.26 shows the plane pattern of the storage capacitance part in the embodiment. The storage

capacitance ~~consists of~~ is formed by the scanning line or the storage line in the same layer as the scanning line, a part of the picture element and the gate insulating film. Since the scanning line and the picture element electrode lie in ~~the~~ different layers, the storage capacitance depends on places of the panel due to the inaccuracy of photo-mask alignment, which changes the bias voltage. The bias voltage variation induces the brightness non-uniformity in the block state. By ~~the~~ this embodiment, as shown in Fig.26, ~~such a~~ plane pattern is presented as the intersecting area of the picture element electrode, and the storage line in the same layer as the scanning line does not change even if the photo-mask shifts before and behind, and left and right.

\_\_\_\_\_The present embodiment, in addition to the effects of the embodiment 6, has the effects that the display apparatus can present ~~the~~ a picture without ~~the~~ block non-uniformity.